# **Aboistop** vibrant

Product name: Aboistop vibrant Product model: 3007483 Operating voltage: 3.7V Batter v capacity: 300mAh Rated input : DC 5V / 1A Waterproof rating: IP67 Operating temperature: -10°C~+50°C

Storage temperature: -20°C~+60°C Device volume: 70mm\*37mm\*40mm

Net weight: 71a















## First Time Using

- The default setting of this product is: sensitivity sensor level 6. vibration level 3.
- Fully charge the battery before using the first time. In standby mode, touch the button (M) to view the charge level (more details please see page 9 Battery Power).
- Tip

Please read the user manual carefully before use and register it in a safe place!



### Warning

- Product wearing time is recommended no more than 12 hours/day.
- For pets ranging from 5kg-50kg (11lbs~110lbs) and neck circumference up to 62cm (25in). Not suitable for dogs less than 5kg (11lbs) or younger than 6
- Children should not play with this product. Keep it away from children. - 1 -



### **User Operation**

# Wearing







Adjust the length of the strap to fit the pet's neck

### Wearing Points







Circumference

# Contents



Bark Training Device & Nylon Collar







- 2 -

User Manual


# **User Operation**

### Power ON & OFF



See Page 9 for instructions to enter setting mode.


### Functions & Displays



\* Short press to toggle through and view these settings and battery level.

### Introduction

### Bark Collar Components





Touching!

# Introduction

Settings are set.

Display goes away.

**User Operation** 

Display , ----

---- function : \* S

HI HIS

Loop

modes

icon

--- display

--- display

## • 2 Working Modes





Functions Setting Process

Short press

Tap 3 times

settina mode

to enter

functions

Tap to adjust

Automatically

exit setting

mode after

3 secs

device

to wake up ---- display

No barking for 5 secs, sleep mode begins.

Training Mode



Dog is barking, training mode activated.

# • 2 Basic Training Methods





Always exists and cannot be cancelled. No level setting.

Vibration



0~7 level output settings. 0 is off. Default is level 3.

# Trigger Methods





1~7 level sensitivity. Default setting is 6.



# User Operation

### Battery Power







\* If the battery indicator is 1, please use product after fully charged.



Automatically shuts down, ---- Display after prompt flashes



If the product is abnormal during use, you can do the following:



Make Sure Tight










# **ABOISTOP**

# **USER MANUAL**

3007483



# **How Does the Device Work?**

# Training Mode



--- Beep lasts 3 secs



\* If the vibration is off, there will be no corresponding display.

# Single Method Execution Order




\* This means that sound, and vibration do not happen simultaneously during barking. First, your dog will hear the sound, then vibration will occur. - 5 -



## **How Does the Device Work?**

## Training Methods Combination



\* For protection, there is a 1 minute pause after 7 triggers, regardless if the dog is still barking.

- 6 -